



PA TR100

TR100 - Line transformer 100/70V -100W Secondary impedance 16-8-4.



Overview

TR100 - Line transformer 100/70V - 100W. Secondary impedance 16-8-4 ohm.

Technical Specifications

Type: Line audio transformer

- Inputs: 100/70V line
- Notes: Max power: 100W
- Secondary impedance: 16/8/4 ohm

Technical specifications and appearances are subject to change without notice and accuracy is not guaranteed. All trademarks are the property of their respective owners. PROEL accepts no liability for any loss which may be suffered by any person who relies either wholly or in part upon any description, photograph or statement contained herein. Colors and specifications may vary from actual product. PROEL products are sold through authorized fullfillers and resellers only. This manual is copyrighter. No part of this manual may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording of any kind, for any purpose, without the express written permission of PROEL - Via alla Ruenia 37/43 - CAP 64027 - Sant'Omero (TE) ITALY.

For service, support, or more information contact:

Proel S.p.A.

Via alla Ruenia 37/43

CAP 64027 - Sant'Omero (TE) ITALY

